



Use 78L05 and 79L05



Note that gnd can be isolated or shorted

CD is Ceramic Disc  
 104 is 0.1uF  
 103 is 0.01uF  
 102 is 0.001uF



T1  
 Transformer  
 Pri 35 turns 36 swg  
 Sec 90 turns 36 swg  
 wind pri first  
 Insulation tape between pri and sec  
 wind sec next  
 cover final sec with tape  
 Pot core HK100 OL  
 18mm dia 10mm ht  
 Use a pot core clamp  
 or nylon nut bolt  
 to fix to pcb

Dact Elektrotech		
Phone 6768863 2590, 17th Cross, 8th Main Banashankari 2nd Stage Bangalore 560070		
Title Dual Supply 5V from +5V Power Supply		
Size B	Document Number DACT0021.SCH	Rev 00
Date: Monday, August 11, 2003	Sheet 1	of 1